

Page i

# CRYSTAL UNITS IN METAL HOLDER, BASED ON TYPE T1507,

**FREQUENCY RANGE 2.5 - 50MHZ** 

**ESCC Detail Specification No. 3501/019** 

(Follow-up Specification to ESA/SCC Detail Specification Nos. 3501/002 and 3501/009)

# ISSUE 1 October 2002





#### **ESCC Detail Specification**

PAGE ii

ISSUE 1

#### **LEGAL DISCLAIMER AND COPYRIGHT**

European Space Agency, Copyright © 2002. All rights reserved.

The European Space Agency disclaims any liability or responsibility, to any person or entity, with respect to any loss or damage caused, or allleged to be caused, directly or indirectly by the use and application of this ESCC publication.

This publication, without the prior permission of the European Space Ageny and provided that it is not used for a commercial purpose, may be:

- copied in whole in any medium without alteration or modification.
- copied in part, in any medium, provided that the ESCC document identification, comprising the ESCC symbol, document number and document issue, is removed.



# european space agency agence spatiale européenne

Pages 1 to 18

# CRYSTAL UNITS IN METAL HOLDER, BASED ON TYPE T1507,

FREQUENCY RANGE 2.5 - 50MHZ

ESA/SCC Detail Specification No. 3501/019

(Follow-up Specification to ESA/SCC Detail Specification Nos. 3501/002 and 3501/009)



# space components coordination group

		Appro	oved by
Issue/Rev.	Date	SCCG Chairman	ESA Director General or his Deputy
Issue 2	September 2002	71.300	From _



PAGE 2

ISSUE 2

#### **DOCUMENTATION CHANGE NOTICE**

Rev. Rev. Letter Date	Reference	CHANGE Item	Approved DCR No.



PAGE 3

ISSUE 2

#### **TABLE OF CONTENTS**

		<u>Page</u>
1.	<u>GENERAL</u>	5
1.1	Scope	_
1.2	Range of Components	5 5
1.3	Maximum Ratings	5 5
1.4	Physical Dimensions	5
1.5	Functional Diagram	5 5
	· · · · · · · · · · · · · · · · · · ·	3
2.	APPLICABLE DCCUMENTS	5
3.	TERMS, DEFINITIONS, ABBREVIATIONS, SYMBOLS AND UNITS	5
4.	REQUIREMENTS	11
4.1	General	11
4.2	Deviations from Generic Specification	11
4.2.1	Deviations from Special In-process Controls	11
4.2.2	Deviations from Final Production Tests	11
4.2.3	Deviations from Burn-in Tests	11
4.2.4	Deviations from Qualification Tests	11
4.2.5	Deviations from Lot Acceptance Tests	11
4.3	Mechanical Requirements	11
4.3.1	Dimension Check	11
4.3.2	Weight	11
4.3.3	Robustness of Terminations	11
4.4	Materials and Finishes	11
4.4.1	Case	12
4.4.2	Lead Material and Finish	12
4.5	Marking	12
4.5.1	General	12
4.5.2	Characteristics	12
4.5.3	Traceability Information	12
4.5.4	The SCC Component Number	12
4.5.5	Manufacturer's Name, Symbol or Code	13
4.6	Electrical Measurements	13
4.6.1	Electrical Measurements at Reference Temperature	13
4.6.2	Electrical Measurements at High and Low Temperatures	13
4.6.3	Circuits for Electrical Measurements	13
4.7	Burn-in Tests	13
4.7.1	Parameter Drift Values	13
4.7.2	Conditions for Burn-in	13
4.7.3	Electrical Circuits for Burn-in	13
4.8	Environmental and Endurance Tests	15
4.8.1	Measurements and Inspections on Completion of Environmental Tests	15
4.8.2	Measurements and Inspections at Intermediate Points and on Completion of Endurance Tests	15
4.8.3	Conditions for Operating Life Test	15



PAGE 4 ISSUE 2

TABLES	<u> </u>	Page
1(a) 1(b) 2 3 4 5	Format for Individual Tables 1(a) Maximum Ratings Electrical Measurements at Reference Temperature Electrical Measurements at High and Low Temperatures Parameter Drift Values Conditions for Burn-in and LAT Life Tests Measurements and Inspections on Completion of Environmental Tests and at Intermediate Points and on Completion of Endurance Testing	6 9 14 14 15 15
FIGURE	<u>:s</u>	
1 2 3 4 5	Parameter Derating Information Physical Dimensions Functional Diagram Circuits for Electrical Measurements Electrical Circuit for Burn-in and Life Test	N/A 10 10 N/A N/A

APPENDICES (Applicable to specific Manufacturers only)

None.



PAGE 5

2

ISSUE

#### 1. **GENERAL**

#### 1.1 SCOPE

This specification details the values, physical and electrical characteristics, test and inspection data for Crystal Units in Metal Holder, based on Type T1507, Frequency Range 2.5 - 50MHz.

It shall be read in conjunction with ESA/SCC Generic Specification No. 3501, the requirements for which are supplemented herein.

This is a follow-up specification to ESA/SCC Detail Specification Nos. 3501/002 and 3501/009 which should be consulted by:-

- (a) Users seeking information concerning the availability of variants previously ordered to these specifications.
- (b) Manufacturers before introducing a new specific crystal identification as outlined in Para. 1.2.

#### 1.2 RANGE OF COMPONENTS

The specific characteristics shall be negotiated between the Manufacturer and the Orderer on the basis of Table 1(a).

The contents of the individual tables shall relate to the design parameters of individual crystal units, optimised for the intended application.

The agreed table shall be held under configuration control by the Manufacturer who will allocate a specific crystal identification number sequentially when a request for a crystal is received.

#### 1.3 MAXIMUM RATINGS

The maximum ratings, which shall not be exceeded at any time during use or storage, applicable to the crystal units specified herein, are as scheduled in Table 1(b).

#### 1.4 PHYSICAL DIMENSIONS

The physical dimensions of the crystal units specified herein are shown in Figure 2.

#### 1.5 FUNCTIONAL DIAGRAM

The functional diagram showing lead identification of the crystal units specified herein is shown in Figure 3.

#### 2. <u>APPLICABLE DOCUMENTS</u>

The following documents form part of this specification and shall be read in conjunction with it:-

(a) ESA/SCC Generic Specification No. 3501 for Quartz Crystal Units.

#### 3. TERMS, DEFINITIONS, ABBREVIATIONS, SYMBOLS AND UNITS

For the purpose of this specification, the terms, definitions, abbreviations, symbols and units specified in ESA/SCC Basic Specification No. 21300 shall apply. In addition, the following symbols are used:-

Resonance Frequency	= f <sub>r</sub>	Static Capacitance	=	$C_0$
Load Resonance Frequency	= fĹ	Load Capacitance		Ĉi
Reference Temperature	$= T_o$	Motional Capacitance		$C_1$
Turning Point Temperature	$= T_{TP}$	Motional Inductance	=	L <sub>1</sub>
Resonance Resistance	$= R_r$	Response Resistance	=	$R_{P}$
Load Resonance Resistance	$= R_L$	Response Impedance	=	ΙΖ <sub>Ρ</sub> Ι
Rated Drive Level	= P <sub>o</sub>	Insulation Resistance	=	Ri



PAGE 6

ISSUE 2

#### TABLE 1(a) - FORMAT FOR INDIVIDUAL TABLES 1(a)

#### SPECIFIC CRYSTAL IDENTIFICATION NUMBER -

Resonance Frequency			_	Lir	nits			
$ \begin{array}{c ccccccccccccccccccccccccccccccccccc$	No.	Characteristic	Symbol	Min.	Мах	Unit	Remarks	
3   Turning Point Temperature   T <sub>TP</sub>   °C   Note 3	1	Resonance Frequency	f <sub>r</sub> or f <sub>L</sub>			MHz	Note 1	
4   Overtone Order   -	2	Reference Temperature	T <sub>o</sub>			°C	Note 2	
5   Load Capacitance   C <sub>L</sub>   pF   Note 4     6   Rated Drive Level   P <sub>o</sub>   mW   Note 5     7   Frequency Adjustment Tolerance   Af   f   10-6   At T <sub>o</sub> °C Note 6     8   Resonance Resistance   R <sub>f</sub> or R <sub>L</sub>   Ω   At T <sub>o</sub> °C Note 7     9   Frequency Variation with Temperature over T <sub>op</sub>   From frequency measured at T <sub>o</sub> °C Note 8     10   Resistance Variation with Temperature over T <sub>op</sub>   Promagneture over T <sub>op</sub>   °C     11   Operating Temperature Range   T <sub>op</sub>   °C     12   Frequency Variation with Drive Level   Af   From P <sub>S1</sub> = m to P <sub>S2</sub> = m Note 9     13   Resistance Variation with Drive Level   Af   R   R   Prom P <sub>S1</sub> = m to P <sub>S2</sub> = m Note 9     14   Motional Inductance   L <sub>1</sub>   mH   Notes 10 and 11     15   Motional Capacitance   C <sub>0</sub>   pF   Note 10     17   Q Factor   Q   - Notes 10 and 12     18   Ratio of Unwanted:   In the frequency   In the	3	Turning Point Temperature	T <sub>TP</sub>		-	°C	Note 3	
Resistance Variation with Drive Level	4	Overtone Order	-					
7   Frequency Adjustment Tolerance   At To °C Note 6     8   Resonance Resistance   Rr or RL   Ω   At To °C Note 7     9   Frequency Variation with Temperature over Top   Resistance Variation with Temperature over Top   Resistance Variation with Drive Level   Tolerance   At R   R     10   Qperating Temperature Range   Tolerance   At R   R     10   Resistance Variation with Drive Level   Tolerance   At R   R     10   Tolerance   Tol	5	Load Capacitance	C <sub>L</sub>			pF	Note 4	
8         Resonance Resistance         R <sub>r</sub> or R <sub>L</sub> Ω         At T <sub>o</sub> °C Note 7           9         Frequency Variation with Temperature over T <sub>op</sub> Δf         10°         From frequency measured at T <sub>o</sub> °C Note 8           10         Resistance Variation with Temperature over T <sub>op</sub> ΔR/R         %         From resistance measured at T <sub>o</sub> °C Note 8           11         Operating Temperature Range         Top         °C           12         Frequency Variation with Drive Level         Δf/f         10°-6         From P <sub>S1</sub> = m Note 9           13         Resistance Variation with Drive Level         AR/R         %         From P <sub>S1</sub> = m Note 9           14         Motional Inductance         L <sub>1</sub> mH         Notes 10 and 11           15         Motional Capacitance         C <sub>1</sub> fF         Note 10           16         Static Capacitance         C <sub>0</sub> pF         Note 10           17         Q Factor         Q         -         Notes 10 and 12           18         Ratio of Unwanted:         In the frequency	6	Rated Drive Level	Po		-	mW	Note 5	
9       Frequency Variation with Temperature over Top       Δf f f       10-9       From frequency measured at To °C Note 8         10       Resistance Variation with Temperature over Top       ΔR R       %       From resistance measured at To °C Note 8         11       Operating Temperature Range       Top       °C         12       Frequency Variation with Drive Level       Δf f       10-6       From Ps1 = m to Ps2 = m Note 9         13       Resistance Variation with Drive Level       ΔR R       %       From Ps1 = m to Ps2 = m Note 9         14       Motional Inductance       L1 mH Notes 10 and 11         15       Motional Capacitance       C1 fF Note 10         16       Static Capacitance       C0 pF Note 10         17       Q Factor       Q       - Notes 10 and 12         18       Ratio of Unwanted:       In the frequency	7		<u>Δ f</u> f			10 <sup>-6</sup>		
with Temperature over Top       f       measured at T₀ °C Note 8         10       Resistance Variation with Temperature over Top       ΔR/R       %       From resistance measured at T₀ °C Note 8         11       Operating Temperature Range       Top       °C         12       Frequency Variation with Drive Level       Δf/f       10-6       From Ps₁ = m to Ps₂ = m Note 9         13       Resistance Variation with Drive Level       ΔR/R       %       From Ps₁ = m to Ps₂ = m Note 9         14       Motional Inductance       L₁       mH       Notes 10 and 11         15       Motional Capacitance       C₁       fF       Note 10         16       Static Capacitance       C₀       pF       Note 10         17       Q Factor       Q       -       Notes 10 and 12         18       Ratio of Unwanted:       In the frequency	8	Resonance Resistance	R <sub>r</sub> or R <sub>L</sub>			Ω	At To °C Note 7	
with Temperature over Top         R         measured at T₀ °C Note 8           11 Operating Temperature Range         Top         °C           12 Frequency Variation with Drive Level         Δf f         10-6         From P₃1 = m to Note 9           13 Resistance Variation with Drive Level         ΔR R         % From P₃1 = m to Note 9           14 Motional Inductance         L₁         mH Notes 10 and 11           15 Motional Capacitance         C₁         fF Note 10           16 Static Capacitance         C₀         pF Note 10           17 Q Factor         Q         - Notes 10 and 12           18 Ratio of Unwanted:         In the frequency	9	with Temperature	∆ f f			10 <sup>-9</sup>	measured at To °C	
12   Frequency Variation with Drive Level	10	with Temperature	<u>∆ R</u> R			%	measured at To °C	
with Drive Level  To P <sub>S2</sub> = m Note 9  13 Resistance Variation with Drive Level  Motional Inductance  L <sub>1</sub> Motional Capacitance  C <sub>1</sub> Motional Capacitance  C <sub>0</sub> The Static Capacitance  C <sub>0</sub> Resistance Variation with Drive Level  MH Notes 10 and 11  The Static Capacitance  C <sub>0</sub> The Note 10  The Static Capacitance  C <sub>0</sub> The Note 10  The Static Capacitance  C <sub>0</sub> The Note 10  The Static Capacitance  The Note 10 and 12  Th	11	Operating Temperature Range	T <sub>op</sub>			°C		
with Drive Level         R         to P <sub>S2</sub> = m Note 9           14 Motional Inductance         L <sub>1</sub> mH         Notes 10 and 11           15 Motional Capacitance         C <sub>1</sub> fF         Note 10           16 Static Capacitance         C <sub>0</sub> pF         Note 10           17 Q Factor         Q         -         Notes 10 and 12           18 Ratio of Unwanted:         In the frequency	12	Frequency Variation with Drive Level				10-6	to	
15     Motional Capacitance     C1     fF     Note 10       16     Static Capacitance     Co     pF     Note 10       17     Q Factor     Q     -     Notes 10 and 12       18     Ratio of Unwanted:     In the frequency	13		<u>∆ R</u> R			%	to P <sub>S2</sub> = mW	
16     Static Capacitance     Co     pF     Note 10       17     Q Factor     Q     -     Notes 10 and 12       18     Ratio of Unwanted:     In the frequency	14	Motional Inductance	L <sub>1</sub>			mH	Notes 10 and 11	
17 Q Factor Q - Notes 10 and 12 18 Ratio of Unwanted: In the frequency	15	Motional Capacitance	C <sub>1</sub>			fF	Note 10	
18 Ratio of Unwanted: In the frequency	16	Static Capacitance	Co			pF	Note 10	
	17	Q Factor	Q			-	Notes 10 and 12	
Resonance Resistance R <sub>p</sub> /R to	18	Response Resistance to Resonance Resistance or Response Impedance to	òr				range: f - kHz to f + kHz	
19 Ageing Δ f f 10-6 Note 14	19	Ageing	Δf f			10 <sup>-6</sup>	Note 14	
20 Lead Finish	20	Lead Finish	-			-		
21 Intended Application Note 15	21	Intended Application					Note 15	

NOTES: See Pages 7 and 8.



PAGE

ISSUE 2

7

#### **NOTES TO TABLE 1(a)**

- 1. Resonance Frequency fr or fL
  - (a) If C<sub>L</sub> is not specified, Symbol and measurement shall be f<sub>r</sub>.
  - (b) If C<sub>L</sub> is specified, Symbol and measurement shall be f<sub>L</sub>.
- 2. Reference Temperature To
  - (a) For a crystal unit functioning in a non-controlled temperature environment, the reference temperature is normally +25 ±2 °C.
- Turning Point Temperature T<sub>TP</sub>
  - (a) For a crystal unit functioning in a temperature controlled environment (OCXO), the turning point temperature shall be within the limits specified for the reference temperature range.
  - (b) To be specified for OCXO crystal units in addition to the reference temperature.
- 4. Load Capacitance CL
  - (a) When a crystal unit must function at its series resonance frequency, C<sub>L</sub> shall be infinite.
  - (b) When a crystal unit must function with a fixed load capacitance, the C<sub>L</sub> value shall be specified.
  - (c) When a crystal unit must function with an adjustable load capacitance, the minimum and maximum limits shall be specified.

#### N.B.

The tolerance on the load capacitance shall be that value which results in a frequency change not exceeding 10% of the frequency tolerance at  $T_0$  or 1% of the nominal load capacitance, whichever is smaller.

#### Rated Drive Level Po

The rated drive level shall be selected from the standard drive levels specified below:

- 0.25mW, 0.2mW, 0.1mW, 0.05mW, 0.02mW and 0.01mW ±20%.

#### 6. Frequency Adjustment Tolerance

- (a) When a crystal unit must function at its series resonance frequency, the resonance frequency measured at  $T_0$  shall be within the tolerance specified. The standard value of the adjustment tolerance shall be  $\pm 10 \times 10^{-6}$ .
- (b) When a crystal unit has to function with a fixed load capacitance, the resonance frequency measure with this load at  $T_0$  shall be within the tolerance specified. The standard value of the adjustment tolerance shall be  $\pm 10 \times 10^{-6}$ .
- (c) When a crystal unit is required to operate with an adjustable load capacitance with the limits indicated in Item 5 of the Table, the resonance frequency shall be adjustable to its correct T<sub>0</sub> value so the frequency adjustment tolerance does not need to be specified.

#### 7. Resonance Resistance

- (a) Generally, the maximum value only is specified.
- (b)  $R_L$  may be calculated by  $R_L = R_r \left( 1 + \frac{C_0}{C_L} \right)^2$ .
- 8. Frequency and Resistance Variation with Temperature

These values shall be specified such that they are consistent with the operating temperature range.



PAGE

ISSUE 2

8

#### NOTES TO TABLE 1(a) (Continued)

#### 9. Frequency and Resistance Variation with Drive Level

These limits and the Drive Level range (PS1 to PS2) shall be specified for very special crystals only (i.e. crystals used in very high stability oscillators).

#### 10. Electrical Values

The electrical values shall be specified only when required for the correct functioning of the equipment in which the crystal is used.

#### 11. Motional Inductance L<sub>1</sub>

Because the inductance value may be restricted by other chosen parameters, the Manufacturer shall propose the value of L<sub>1</sub> in accordance with the Customer's requirements.

#### 12. 'Q' Factor

If 'R' and 'L' have been already specified, it will not be necessary to specify the minimum value of the 'Q' factor.

The maximum value of the 'Q' factor is never specified.

#### 13. Ratio of Unwanted Response Resistance to Resonance Resistance

The standard minimum value is 2, but it is possible to obtain higher values.

The frequency range within which the minimum value of the ratio is required shall also be specified.

#### 14. Ageing

Specify limits under appropriate column and ageing period under "Remarks".

#### 15. Intended Application

For definitions of the selected symbols to be added, see ESA/SCC Generic Specification No. 3501, Para. 3.

#### 16. Not Applicable Items

For all items where limits are not specified, "Not applicable" shall be entered in the Limits column.



PAGE 9 ISSUE 2

#### **TABLE 1(b) - MAXIMUM RATINGS**

No.	Characteristic	Symbol	Values	Unit	Remarks
1	Nominal Frequency Range	f	2.5 to 20	MHz	Note 1
2	Drive Level Range	Р	0.01 to 0.2	mW	Note 1
3	Operating Temperature Range	Тор		°C	Note 2
4	Storage Temperature Range	T <sub>stg</sub>	-65 to +125	°C	Note 3
5	Soldering Temperature	T <sub>sol</sub>	+260	°C	Note 4

#### **NOTES**

4	
ı	

Fundamental and Overtone Order	Approx. Frequency Range (MHz)	Drive Level Range (mW)
Fundamental	2.5 to 20	0.05 to 0.2
3	10 to 30	0.05 to 0.25
5	15 to 50	0.05 to 0.25

In use, the rated drive level shall not be exceeded.

- 2. See Tables 1(a).
- 3. The duration at maximum storage temperature shall not exceed 16 hours.
- 4. Duration 10 seconds maximum at a distance of not less than 3.0mm from the device body and the same lead shall not be resoldered until 3 minutes have elapsed.



PAGE 10

ISSUE 2

#### FIGURE 1 - PARAMETER DERATING INFORMATION


Not applicable.


#### **FIGURE 2 - PHYSICAL DIMENSIONS**

SYMBOL	MILLIM	ETRES	REMARKS
STIVIDOL	MIN.	MAX.	REWARKS
⊘A	_	15.75	
С	-	6.80	
Н	6.90	7.40	Pitch 7.16mm
⊘K	0.40	0.48	
L	12.70	_	
Р	_	0.90	Note 2
Q		0.95	Note 2

#### **NOTES**


- 1. Lead No. 5 is grounded to case.
- 2. The tag's position or presence is optional.





ØΑ

#### **FIGURE 3 - FUNCTIONAL DIAGRAM**



(BOTTOM VIEW)



PAGE 11

ISSUE 2

#### 4. **REQUIREMENTS**

#### 4.1 GENERAL

The complete requirements for procurement of the crystal units specified herein shall be as stated in this specification and ESA/SCC Generic Specification No. 3501 for Quartz Crystal Units. Deviations from the Generic Specification applicable to this specification only, are detailed in Para. 4.2.

Deviations from the applicable Generic Specification and this Detail Specification, formally agreed with specific Manufacturers on the basis that the alternative requirements are equivalent to the ESA/SCC requirements and do not affect the components' reliability, are listed in the appendices attached to this specification.

#### 4.2 DEVIATIONS FROM GENERIC SPECIFICATION

#### 4.2.1 <u>Deviations from Special In-process Controls</u>

None.

#### 4.2.2 <u>Deviations from Final Production Tests (Chart II)</u>

None.

#### 4.2.3 <u>Deviations from Burn-in Tests (Chart III)</u>

None.

#### 4.2.4 <u>Deviations from Qualification Tests (Chart IV)</u>

None.

#### 4.2.5 <u>Deviations from Lot Acceptance Tests (Chart V)</u>

None.

#### 4.3 MECHANICAL REQUIREMENTS

#### 4.3.1 <u>Dimension Check</u>

The dimensions of the crystal units specified herein shall be checked. They shall conform to those shown in Figure 2.

#### 4.3.2 Weight

The maximum weight of the crystal units specified herein shall be 3.0 grammes.

#### 4.3.3 Robustness of Terminations

The requirements for robustness of termination testing are specified in Section 9 of ESA/SCC Generic Specification No. 3501.

#### 4.4 MATERIALS AND FINISHES

The materials and finishes shall be as specified herein. Where a definite material is not specified, a material which will enable the crystal units specified herein to meet the performance requirements of this specification shall be used. Acceptance or approval of any constituent material does not guarantee acceptance of the finished product.



PAGE 12

ISSUE 2

#### 4.4.1 Case

#### 4.4.1.1 Cap

Copper, nickel plated or nickel and gold plated.

#### 4.4.1.2 Base

Kovar, nickel plated or nickel and gold plated.

#### 4.4.2 Lead Material and Finish

The lead material shall be Type 'D' with either Type '2' (Variant 01) or Type '3 or 4' (Variant 02) finish in accordance with the requirements of ESA/SCC Basic Specification No. 23500. (See Tables 1(a) for Type Variants).

#### 4.5 MARKING

#### 4.5.1 General

The marking of all components delivered to this specification shall be in accordance with the requirements of ESA/SCC Basic Specification No. 21700 and the following paragraphs. When the component is too small to accommodate all of the marking specified, as much as space permits shall be marked and the marking information, in full, shall accompany the component in its primary package.

The information to be marked and the order of precedence, shall be as follows:-

- (a) Characteristics.
- (b) Traceability Information.
- (c) The SCC Component Number.

#### 4.5.2 Characteristics

The characteristics to be marked are the frequency and the specific crystal identification number.

#### 4.5.2.1 Frequency

The resonance frequency of the crystal units shall be clearly specified in MHz. Where necessary, it shall be specified to 6 decimal places.

#### 4.5.2.2 Specific Crystal Identification Number

This identification shall be allocated by the Manufacturer (see Para. 1.2) and shall consist of the following:

- Letter

First letter of the crystal manufacturer's name.

4 digit number :

Sequentially allocated by each Manufacturer.

#### 4.5.3 Traceability Information

Each component shall be marked in respect of traceability information in accordance with the requirements of ESA/SCC Basic Specification No. 21700.

#### 4.5.4 The SCC Component Number

Each component shall bear the SCC Component Number, which shall be constituted and marked as follows:-

Detail Specification Number	
Type Variant (see Para. 4.4.2)	
Testing Level (B or C, as applicable)	



PAGE 13

ISSUE 2

#### 4.5.5 Manufacturer's Name, Symbol or Code

The Manufacturer's marking shall be in accordance with the requirements of ESA/SCC Basic Specification No. 21700.

#### 4.6 ELECTRICAL MEASUREMENTS

#### 4.6.1 <u>Electrical Measurements at Reference Temperature</u>

The parameters to be measured in respect of electrical characteristics are scheduled in Table 2.

The measurements shall be performed at the temperatures specified in the individual Tables 1(a), Item 2.

Measurements at reference temperature for OCXO crystals shall be performed at T<sub>TP</sub> ± 1°C.

#### 4.6.2 <u>Electrical Measurements at High and Low Temperatures</u>

The parameters to be measured at high and low temperatures are scheduled in Table 3. These measurements shall only be performed if values are specified in Tables 1(a) Items 9 and/or 10.

#### 4.6.3 <u>Circuits for Electrical Measurements (Figure 4)</u>

Not applicable.

#### 4.7 BURN-IN TESTS

#### 4.7.1 Parameter Drift Values

The parameter drift values applicable to burn-in are specified in Table 4 of this specification. Unless otherwise stated, measurements shall be performed at  $T_{amb} = T_0 \pm 2$  °C. The parameter drift values (Delta) applicable to the scheduled parameters shall not be exceeded. In addition to these drift value requirements for a given parameter, the appropriate limit value specified in Table 2 shall not be exceeded.

#### 4.7.2 Conditions for Burn-in

The requirements for burn-in are specified in Section 7 of ESA/SCC Generic Specification No. 3501.

The test shall be performed as a high temperature storage test and the temperature to be applied shall be as specified in Table 5 of this specification.

For a crystal unit functioning in a temperature controlled environment (OCXO), the test should preferably be performed as an operating life test in an oscillator, at the Turning Point Temperature, with a daily measurement of the resonance frequency of the oscillator.

#### 4.7.3 Electrical Circuits for Burn-in (Figure 5)

Not applicable.



PAGE 14

ISSUE 2

#### TABLE 2 - ELECTRICAL MEASUREMENTS AT REFERENCE TEMPERATURE

	T	T	г		
No.	Characteristics	Symbol	ESA/SCC 3501 Test Method	Limits	Unit
1	Resonance frequency at reference temperature and rated drive level - with C <sub>O</sub> - with C <sub>L</sub>	f <sub>r</sub> (T <sub>o</sub> , P <sub>o</sub> ) f <sub>L</sub> (T <sub>o</sub> , P <sub>o</sub> )	Para. 9.2.1.1	Table 1(a), Item 1 ± Item 7	MHz
2	Resonance resistance at reference temperature and rated drive level - with C <sub>O</sub> - with C <sub>L</sub>	R <sub>r</sub> (T <sub>o</sub> , P <sub>o</sub> ) R <sub>L</sub> (T <sub>o</sub> , P <sub>o</sub> )	Para. 9.2.1.1	Table 1(a), Item 8	Ω
3	Frequency variation with Drive Level	$\frac{\Delta f}{f}$ (T <sub>o</sub> , $\Delta P$ )	Para. 9.2.1.1	Table 1(a), Item 12	10-6
4	Resistance variation with Drive Level	<u>Δ R</u> (T <sub>o</sub> , ΔP)	Para. 9.2.1.1	Table 1(a), Item 13	%
5	Motional Inductance	L <sub>1</sub>	Para. 9.2.1.3	Table 1(a), Item 14	mH
6	Static Capacitance	C <sub>o</sub>	Para. 9.2.1.4	Table 1(a), Item 16	pF
7	Unwanted response	R <sub>P</sub> /R or IZ <sub>P</sub> I/R	Para. 9.2.1.5	Table 1(a), Item 18	<u>.</u>
8	Insulation Resistance	Ri	Para. 9.2.1.6	500 Min.	МΩ

#### TABLE 3 - ELECTRICAL MEASUREMENTS AT HIGH AND LOW TEMPERATURES

No.	Characteristics	Symbol	ESA/SCC 3501 Test Method	Limits	Unit
9	Frequency variation with Temperature over Top	<u>Δ f</u> (ΔΤ, P <sub>o</sub> )	Para. 9.2.1.2	Table 1(a) Item 9	10-6
10	Resistance variation with Temperature over Top	$\frac{\Delta R}{R}$ ( $\Delta T$ , $P_0$ )	Para. 9.2.1.2	Table 1(a) Item 10	%

#### FIGURE 4 - CIRCUITS FOR ELECTRICAL MEASUREMENTS

Not applicable.



PAGE 15

ISSUE 2

#### **TABLE 4 - PARAMETER DRIFT VALUES**

No.	Characteristics	Symbol	Spec. and/or Test Method	Test Conditions	Change Limits (Δ)	Unit
1	Resonance frequency drift	Δf f	As per Table 2	As per Table 2	± 2.0	10-6
2	Resonance resistance drift	<u>∆ R</u> R	As per Table 2	As per Table 2	± 10 or (1) ± 1.0	% Ω

#### NOTES

1. Whichever is the highest value.

#### TABLE 5 - CONDITIONS FOR BURN-IN AND LAT LIFE TESTS

No.	Characteristics	Symbol	Condition (Note 1)	Unit
1	Ambient Temperature	T <sub>amb</sub>	+ 105 (+0-5)	°C

#### **NOTES**

1. See Para. 4.7.2

#### FIGURE 5 - ELECTRICAL CIRCUIT FOR BURN-IN AND LIFE TEST

Not applicable.

## 4.8 <u>ENVIRONMENTAL AND ENDURANCE TESTS (CHARTS IV AND V OF ESA/SCC GENERIC SPECIFICATION NO. 3501)</u>

#### 4.8.1 <u>Measurements and Inspections on Completion of Environmental Tests</u>

The parameters to be measured and inspections to be performed on completion of environmental tests are scheduled in Table 6. Unless otherwise stated, the measurements shall be performed at  $T_{amb} = T_0 \pm 2$  °C.

#### 4.8.2 Measurements and Inspections at Intermediate Points and on Completion of Endurance Tests

The parameters to be measured and inspections to be performed at intermediate points and on completion of endurance tests are scheduled in Table 6. Unless otherwise stated, the measurements shall be performed at  $T_{amb} = T_0 \pm 2$  °C.

#### 4.8.3 Conditions for Operating Life Test (Part of Endurance Testing)

The requirements for the operating life test are specified in Section 9 of ESA/SCC Generic Specification No. 3501. The test shall be performed as a high temperature storage test and the test temperatures are specified in ESA/SCC Generic Specification No. 3501 for Qualification Testing and in Table 5 of this specification for LAT Testing.

For a crystal unit functioning in a temperature controlled environment (OCXO), the test should preferably be performed as an operating life test in an oscillator, at the Turning Point Temperature, with a daily measurement of the resonance frequency of the oscillator.



PAGE 16

ISSUE 2

## TABLE 6 - MEASUREMENTS AND INSPECTIONS ON COMPLETION OF ENVIRONMENTAL TESTS AND AT INTERMEDIATE POINTS AND ON COMPLETION OF ENDURANCE TESTING

	ESA/SCC GENERIC SPEC. NO. 3501		MEASUREMENTS A		LIMITS			
NO.	ENVIRONMENTAL AND ENDURANCE TESTS (1)	TEST METHOD AND CONDITIONS	IDENTIFICATION	CONDITIONS	SYMBOL	Min.	Max.	UNIT
01	Electrical Measurements at Reference Temperature	Para. 9.2.4	Electrical Measurements	Table 2		Tabl	e 1(a)	
02	Shock	Para. 9.3	Initial Measurements Resonance Frequency Resonance Resistance Final Measurements Resonance Frequency Drift Resonance Resistance Drift	Table 2 Item 1 Table 2 Item 2 Table 2 Item 1	f R <u>Δf</u> f <u>ΔR</u> R ΔR		2 Item 1 2 Item 2 +1.0 +10 +1.0	10 <sup>-6</sup> % Ω
03	Vibration	Para. 9.4	Initial Measurements Resonance Frequency Resonance Resistance Final Measurements Resonance Frequency Drift Resonance Resistance Drift	Table 2 Item 1	f R <u>Δf</u> f ΔR R ΔR		2 Item 1 2 Item 2 +1.0 +10 +1.0	10 <sup>-6</sup> % Ω
04	Seal Test	Para. 9.5	Fine Leak Gross Leak	Para. 9.5.1 Para. 9.5.2			. 9.5.1 . 9.5.2	
05	Permanence of Marking	Para. 9.8	Final Measurements Visual Examination	No corrosion or obliteration of marking	-	-	-	-
06	External Visual Inspection	Para. 9.9	Final Measurements Visual Inspection	ESA/SCC No. 20500	-	-	-	-
07	Solderability	Para. 9.13	-	-	-	-	-	-

#### **NOTES**

- 1. The tests in this table refer to either Chart IV or V, and shall be used as applicable.
- 2. Whichever is the highest value.



PAGE 17

ISSUE 2

### TABLE 6 - MEASUREMENTS AND INSPECTIONS ON COMPLETION OF ENVIRONMENTAL TESTS AND AT INTERMEDIATE POINTS AND ON COMPLETION OF ENDURANCE TESTING (Cont.)

	ESA/SCC GENERIC S	PEC. NO. 3501	MEASUREMENTS A	ND INSPECTIONS		LIMITS		
NO.	ENVIRONMENTAL AND ENDURANCE TESTS (1)	TEST METHOD AND CONDITIONS	IDENTIFICATION	CONDITIONS	SYMBOL	Min.	Max.	UNIT
	Climatic Sequence	Para. 9.14		*				
08	Dry Heat	Para. 9.14.1	Initial Measurements				•	
			Resonance Frequency	Table 2 Item 1	f		2 Item 1	
			Resonance Resistance	Table 2 Item 2	R	Table	2 Item 2	
			Final Measurements Resonance Frequency	Table 2 Item 1	۸.	-2.0	+ 2.0	10-6
			Drift	Table 2 item i	$\frac{\Delta f}{f}$	-2.0	T 2.0	10-0
			Resonance Resistance	Table 2 Item 2	<u>Δ R</u>	-10	+10	%
			Drift		R	or (2)		
					ΔR	- 1.0	+ 1.0	Ω
09	Cold	Para. 9.14.3	Initial Measurements			l <u>.</u> .		1
			Resonance Frequency Resonance Resistance	Table 2 Item 1 Table 2 Item 2	f R		9.14.1.3 asurements	
			Final Measurements	Table 2 Item 2	_ n	I IIIai Mea	1501611161115	
			Resonance Frequency	Table 2 Item 1	Δf	-2.0	+ 2.0	10-6
			Drift		<u>Δ f</u> f			
			Resonance Resistance	Table 2 Item 2	<u>Δ R</u>	-10	+10	%
			Drift		R	or (2)		
10	Damp Heat (Acclerated)	Para, 9.14.4	Initial Measurements		ΔR	-1.0	+1.0	Ω
'0	Remaining Cycles	Faia. 9.14.4	Resonance Frequency	Table 2 Item 1	l f	Para	9.14.3.2	
1	Tromaining Oyoloo		Resonance Resistance		Ŕ		asurements	
			Final Measurements					
			Resonance Frequency Drift	Table 2 Item 1	Δf f	-2.0	+ 2.0	10-6
			Resonance Resistance	Table 2 Item 2	<u>Δ R</u>	-10	+10	%
			Drift		R	or (2)		
			Insulation Resistance	Table 2 Item 8	∆R Ri	-1.0 500	+1.0	$\Omega$ M $\Omega$
			inodiation registerio	Table 2 Helli 6	'"	300		10125
11	Rapid Change of	Para. 9.15	Initial Measurements			_	ŀ	
	Temperature		Resonance Frequency Resonance Resistance	Table 2 Item 1 Table 2 Item 2	l f R		9.14.4.2 asurements	
			Final Measurements	After minimum	"	Fillal Mea	asurements 	
			i mai moadaromonio	Recovery of 2 hours				
			Resonance Frequency	Table 2 Item 1	<u>∆ f</u>	-2.0	+2.0	10-6
			Drift		f			
			Resonance Resistance	Table 2 Item 2	ΔR	-10	+10	%
			Drift		R	or (2)		
					ΔR	- 1.0	+1.0	Ω
12	Robustness of Terminations	Para. 9.16	Tensile Strength	Gen. 3501 Para. 9.16.1				
	1 Strini Guorio		Visual Examination	No visible damage	1			
			Bending	Gen. 3501				
				Para. 9.16.2				
			Visual Examination	No visible damage				

#### <u>NOTES</u>

- 1. The tests in this table refer to either Chart IV or V, and shall be used as applicable.
- 2. Whichever is the highest value.



PAGE 18

ISSUE 2

### TABLE 6 - MEASUREMENTS AND INSPECTIONS ON COMPLETION OF ENVIRONMENTAL TESTS AND AT INTERMEDIATE POINTS AND ON COMPLETION OF ENDURANCE TESTING (Cont.)

NO.	ESA/SCC GENERIC SPEC. NO. 3501		MEASUREMENTS AND IN		LIMITS			
NO.	ENVIRONMENTAL AND ENDURANCE TESTS (1)	TEST METHOD AND CONDITIONS	IDENTIFICATION	CONDITIONS	SYMBOL	Min.	Мах.	UNIT
13	Life Test	Para. 9.17	Initial Measurements Resonance Frequency Resonance Resistance	Table 2 Item 1 Table 2 Item 2	f R	Table 2	ltem 1 Item 2	
			Intermediate Measurements Resonance Frequency Drift	Table 2 Item 1	∆f f	-2.0	+2.0	10-6
			Resonance Resistance Drift	Table 2 Item 2	<u>Δ R</u> R ΔR	-10 or (2) -1.0	+10	% Ω
			Intermediate Measurements (Chart IV) and Final Measurements (Chart V)	At 1000 hours	ΔN	- 1.0	+1.0	75
			Resonance Frequency Drift	Table 2 Item 1	<u>Δ f</u> f	- 2.5	+ 2.5	10-6
			Resonance Resitance Drift	Table 2 Item 2	<u>Δ R</u> R ΔR	-10 or (2) -1.0	+ 10 + 1.0	% Ω
			Final Measurements (Chart IV)	At 2000 hours		1.0	1.0	
			Resonance Frequency Drift	Table 2 Item 1	<u>Δ f</u>	-3.0	+3.0	10-6
			Resonance Resistance Drift	Table 2 Item 2	<u>Δ R</u> R ΔR	-10 or (2) -1.0	+10	% Ω

#### **NOTES**

- 1. The tests in this table refer to either Chart IV or V, and shall be used as applicable.
- 2. Whichever is the highest value.